

remcom

Description

Remote Commander Emulation

Syntax

remcom {0-255*} (remcon is also available.)

*Values which are listed below are only used

Selective Parameter

None

Typed Parameter

None

Return Value

None

Remote Commander Code Table-

Code	Description	Remarks
0	1	Numeric key
1	2, A,B,C	Numeric key
2	3, D,E,F	Numeric key
3	4, G,H,I	Numeric key
4	5, K,L,M	Numeric key
5	6, M,N,O	Numeric key
6	7, P,Q,R,S	Numeric key
7	8, T,U,V	Numeric key
8	9, W,X,Y,Z	Numeric key
9	0	Numeric key
10	*	
11	#, .(DOT)	
16	MIC	ON/OFF toggle
17	CONNECT	
18	VOLUME +	
19	VOLUME -	

21	Power	
23	CAMERA	
30	ZOOM TELE	
31	ZOOM WIDE	
45	DISCONNECT	
52	BACK SPACE	
58	TOOLS	
65	VIDEO INPUT	
95	F1	Function key
96	F2	Function key
97	F3	Function key
98	F4	Function key
102	RETURN	
104	LAYOUT	
107	PRESENTATION	
110	ENTER	
111	↑	Cursor moving key
115	→	Cursor moving key
119	↓	Cursor moving key
123	←	Cursor moving key
144	Stops the camera operation command or executes the preset command.	Enter this command immediately after camera operation commands (ZOOM TELE, ZOOM WIDE, ↑, →, ↓, ←)to stop camera operation, or enter this command immediately after the desired preset number to execute the preset command.
192	"1" button pressed longer	Numeric key pressed longer
193	"2" button pressed longer	Numeric key pressed longer
194	"3" button pressed longer	Numeric key pressed longer
195	"4" button pressed longer	Numeric key pressed longer
196	"5" button pressed longer	Numeric key pressed longer
197	"6" button pressed longer	Numeric key pressed longer